

LED Driver 75 W

LED-75



LED Driver with built-in dimmer for 12/24 V DC LED-strips with up to 75 W load. The product can be controlled wirelessly via the app or through other products from Plejd.


- Built-in dimming function.
- Input for local control, using for example a momentary push button or motion sensor.
- Tunable white support for LED-strips with common anode.
- Time functions, such as an astro/time schedule.
- Scenes from phone, tablet, or push button.

The product can be installed on a wall with two screws (not supplied).

Load (CV)

12 V DC	1–40 W
24 V DC	1–75 W

If the load isn't tunable, you may connect it to either of the negative (-) terminals.



MAINS ELECTRICITY

230 V/50 Hz, max 0.5 A

STANDBY POWER

No-load power consumption (P_{no}): N/A
Standby power consumption (P_{sb}): 0.35 W
Networked standby power consumption (P_{net}): 0.35 W

TOTAL PRODUCT WEIGHT

295 g

EFFICIENCY AT FULL-LOAD

90 %

OPERATING TEMPERATURE

-25 to +40 °C
Non-condensing

DIMENSIONS

162x62x34 mm

CABLE AREA

Connections: 0.5–2.5 mm²

PROTECTION

Overtemperature software
Short circuit protection

IP CLASS

IP20

RADIO

2.4 GHz mesh
Bluetooth®
<10 dBm

RADIO RANGE

Approx. 10 m indoors.
The Plejd mesh technology extends the range by allowing the units to communicate with each other.

