

Wireless motion sensor

WMS-01

Our wireless sensor is used to automatically turn on and/ or off lights based on motion. It has a detection range of up to 7 m and a battery with up to 10 years calculated battery lifespan.

The product's practical design enables discrete mounting in the corner of the room using screws or the included double sided tape.

Motion detection can be seamlessly combined with othercontrols in your Plejd system, such as push button, app, and scheduling. Settings are easily made in the Plejd app.



Technical data

PIR (Passive Infrared) Sensor

Detection range* Major motion: 7 m

Minor motion: 3.5 m

*Tested in accordance with IEC 63180

Battery life Estimated battery life up to 10 years

(1xAA lithium battery* included)

*Lithium battery is recommended

to maximize lifespan.

2.2 m +/- 10 cm

Recommended mounting

height

Detection angle 90°

Dimensions 110x31x25 mm

Operating environment 0 to +35 °C

Permissible ambient

temperature

Radio 2.4 GHz mesh Bluetooth®

<10 dBm

Radio range Approx. 10 m indoors.

Battery-powered products do not extend the range of Plejd mesh.





